

Safe shunt (zone Omit) DA250U

This unit is designed to shunt one zone from an alarm system & it is connected between the detector(s) & the control unit.

The unit has a green LED & an internal sounder. It is operated by a remote keyswitch (available separately, if required).

Operating the remote keyswitch shunts (or isolates) the detector(s) from the zone & allows access without causing an alarm. The optional LED shows the keyswitch is operated.

When leaving the zone the remote keyswitch is returned to normal. If the zone which has been shunted is in alarm the sounder will operate & prevent the zone being returned to the system.

When the keyholder has ensured the zone is clear the remote keyswitch can be returned to normal, restoring the zone to full protection, & the optional LED will go out.

Link Options

LK1 OUT = Sounder operates when shunt is on.

LK1 IN = Sounder operates only when zone or tamper is in alarm

LK2 OUT = Tamper loop not shunted.

LK2 IN = Tamper loop shunted with zone loop.

LK3 OUT = Self resetting (real time) when remote keyswitch is in

LK3 IN = Zone alarm latches when remote keyswitch is in normal

