

## QUAD AVI DA280

This unit functions similarly to our single AVI (audio Visual Indicator) DA240.

It has four sets of red & green LEDs plus a common push button & Sounder.

For further details see our sheet covering DA240.

INPUTS - Apply +12 Volts to clear alarm.

INHIBIT - Apply +12 Volts to inhibit all operation.

Link options.

INSERT

LK1 for channel 1 = 2 wire operation.

LK2 for channel 2 = 2 wire operation.

LK3 for channel 3 = 2 wire operation.

LK4 for channel 4 = 2 wire operation.

NOTE:- ONLY one channel may be optioned for 2 wire operation.

DO NOT USE the input terminal associated with this channel.

INSERT

LK5 for channel 1 = Latching operation.

LK6 for channel 2 = Latching operation.

LK7 for channel 3 = Latching operation.

LK8 for channel 4 = Latching operation.

A sounder volume control is fitted to the PCB. Use a small screwdriver to adjust.

